



**Table 18-1 Classical Physics**

### A Bit on Maxwell's Equations

**Prerequisites.**

- Poincaré's Lemma, which says that on  $\mathbb{R}^n$ , every closed form is exact. That is, if  $d\omega = 0$ , then there exists  $\eta$  with  $d\eta = \omega$ .
- Integration by parts:  $\int_{\mathbb{R}^n} \omega \wedge d\eta = -(-1)^{\deg \omega} \int_{\mathbb{R}^n} (d\omega) \wedge \eta$  for compactly supported forms.
- The Hodge star operator  $\star$  which satisfies  $\omega \wedge \star \eta = \langle \omega, \eta \rangle dx_1 \cdots dx_n$  whenever  $\omega$  and  $\eta$  are of the same degree.
- The simplest least action principle: the extremes of  $q \mapsto S(q) = \int_a^b (\frac{1}{2}m\dot{q}^2(t) - V(q(t))) dt$  occur when  $m\ddot{q} = -V'(q(t))$ . That is, when  $F = ma$ .

<b>Maxwell's equations</b>					
I. $\nabla \cdot E = \frac{\rho}{\epsilon_0}$	(Flux of $E$ through a closed surface) = (Charge inside)/ $\epsilon_0$				
II. $\nabla \times E = -\frac{\partial B}{\partial t}$	(Line integral of $E$ around a loop) = $-\frac{d}{dt}$ (Flux of $B$ through the loop)				
III. $\nabla \cdot B = 0$	(Flux of $B$ through a closed surface) = 0				
IV. $c^2 \nabla \times B = \frac{j}{\epsilon_0} + \frac{\partial E}{\partial t}$	$c^2$ (Integral of $B$ around a loop) = (Current through the loop)/ $\epsilon_0$ + $\frac{\partial}{\partial t}$ (Flux of $E$ through the loop)				
<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">Conservation of charge</td> <td></td> </tr> <tr> <td style="text-align: center;"><math>\nabla \cdot j = -\frac{\partial \rho}{\partial t}</math></td> <td>(Flux of current through a closed surface) = <math>-\frac{\partial}{\partial t}</math> (Charge inside)</td> </tr> </table>		Conservation of charge		$\nabla \cdot j = -\frac{\partial \rho}{\partial t}$	(Flux of current through a closed surface) = $-\frac{\partial}{\partial t}$ (Charge inside)
Conservation of charge					
$\nabla \cdot j = -\frac{\partial \rho}{\partial t}$	(Flux of current through a closed surface) = $-\frac{\partial}{\partial t}$ (Charge inside)				
<b>Force law</b>					
$F = q(E + v \times B)$					
<b>Law of motion</b>					
$\frac{d}{dt}(p) = F$ , where $p = \frac{mv}{\sqrt{1-v^2/c^2}}$ (Newton's law, with Einstein's modification)					
<b>Gravitation</b>					
$F = -G \frac{m_1 m_2}{r^2} e_r$					

The Feynman Lectures on Physics vol. II, page 18-2

**The Action Principle.** The *4-Vector Potential* is a compactly supported 1-form  $A$  on  $\mathbb{R}^4$  which extremizes the *action*

$$S_J(A) := \int_{\mathbb{R}^4} \frac{1}{2} \|dA\|^2 dt dx dy dz + J \wedge A$$

where the 3-form  $J$  is the *charge-current*.

**The Euler-Lagrange Equations** in this case are  $d\star dA = J$ , meaning that there's no hope for a solution unless  $dJ = 0$ , and that we might as well (think Poincaré's Lemma!) change variables to  $F := dA$ . We thus get

$$dJ = 0 \quad dF = 0 \quad d\star F = J$$

**These are the Maxwell equations!** Indeed, writing  $F = (E_x dx dt + E_y dy dt + E_z dz dt) + (B_x dy dz + B_y dz dx + B_z dx dy)$  and  $J = \rho dx dy dz - j_x dy dz dt - j_y dz dx dt - j_z dx dy dt$ , we find:

$dJ = 0 \implies$	$\text{div } j = -\frac{\partial \rho}{\partial t}$	"conservation of charge"
$dF = 0 \implies$	$\text{div } B = 0$	"no magnetic monopoles"
	$\text{curl } E = -\frac{\partial B}{\partial t}$	that's how generators work!
$d\star F = J \implies$	$\text{div } E = -\rho$	"electrostatics"
	$\text{curl } B = j - \frac{\partial E}{\partial t}$	that's how electromagnets work!

**Exercise.** Use the Lorentz metric to fix the sign errors.

**Exercise.** Use pullbacks along Lorentz transformations to figure out how  $E$  and  $B$  (and  $j$  and  $\rho$ ) appear to moving observers.

**Exercise.** With  $ds^2 = c^2 dt^2 - dx^2 - dy^2 - dz^2$  use  $S = mc \int_{e_1}^{e_2} (ds + eA)$  to derive Feynman's "law of motion" and "force law".